


- Read all instructions carefully before installing.
- Ensure that power is off on the main panel before starting installation or performing any maintenance.
- Do not install this lighting system in a wet location.
- Do not install any fixture closer than 152mm (6") from any curtain or combustible material.
- Make sure that all screws are properly tightened.

YOU WILL NEED:



- Included in Box:
- 1. Power Supply
 - 2. Trim Ring
 - 3. Luminaire

Semi-Recessed Mounting (Remote Driver)

Recommended ceiling cutout dimension: 53mm (2.08")

- Step 1.** Make ceiling cutout to recommended dimension. Pull line, ground, neutral, and dimming lines through ceiling opening and connect to driver (Fig. 1).
- Step 2.** Pass connected power supply through ceiling opening and secure in ceiling, leaving power wires exposed for later connection to luminaire (Fig. 2).
- Step 3.** Install mounting ring in ceiling, using screws included (Fig. 3).
- Step 4.** Attach safety cable on mounting ring to safety cable on luminaire, using carabiner clip (Fig. 4).
- Step 5.** Connect power wires from power supply in ceiling to luminaire with quick-connector (Fig. 5).

Step 6. Insert luminaire upwards into mounting ring (Fig. 6) and turn luminaire clockwise until you hear a distinct click indicating that tabs are locked into position (Figs. 7 and 8). Luminaire is locked into correct position when tabs are positioned as shown in Fig. 9.




Figure 1




Figure 2




Figure 3




Figure 4




Figure 5




Figure 6




Figure 7




Figure 8





Figure 9



WARNING: LUMINAIRES NOT SUITABLE FOR COVERING WITH THERMAL INSULATING MATERIAL



Minimum Space Requirements	
A	≥ 60mm
B	≥ 20mm
C	≥ 20mm
D	≥ 20mm
E	≥ 20mm
T	5-32mm