

SORAA

Dimming compatibility –

Soraa Optima 230V electronic transformer with Soraa 12V lamps

Table of contents

- General compatibility guidelines.....Page 2
- Dimming compatibility.....Page 3-9
 - With Soraa 12V Vivid MR16 7.5W and 9W lamps.....Page 3-4
 - With Soraa 12V Warm Dim MR16 7.5W lamps.....Page 5
 - With Soraa 12V Brilliant HL MR16 7.5W and 9W lamps.....Page 6
 - With Soraa 12V Vivid AR111 18.5W lampsPage 7-8
 - With Soraa 12V Vivid AR111 12.5W lampsPage 9
 - With Soraa 12V Vivid AR111 6W lamps.....Page 10
 - With Soraa 12V Warm Dim AR111 18.5W lampsPage 11

Scope

This document provides the basic guidelines regarding dimming compatibility of SORAA 12V lamps with the Soraa Optima 230V electronic transformer.

Soraa Optima 230V to 12V electronic transformer

SORAA Optima 230V to 12V is an electronic transformer with no minimum load requirement, which makes it the perfect companion for Soraa 12V lamps.

SORAA Optima 230V Electronic 12V transformer compatibility with SORAA lamps - Lamp Only (no dimmer)					
SORAA lamp	Lamp Power	SKU	Compatibility	Minimum number of lamps per transformer	Maximum number of lamps per transformer
12V MR16 Vivid	7.5W	SM16-07-xxD-9yy-03-S3	PASS	1	5
12V MR16 Vivid	9W	SM16-09-xxD-9yy-03-S3	PASS	1	4
12V MR16 Warm Dim	7.5W	SM16-07-xxDM-9yy/918-01	PASS	1	5
12V MR16 Brilliant HL	7.5W	SM16-07-xxD-8yy-H1	PASS	1	5
12V MR16 Brilliant HL	9W	SM16-09-xxD-8yy-H1	PASS	1	4
12V AR111 Vivid	6W	SR111-06-04D-9yy-03-S3	PASS	1	7
12V AR111 Vivid	12.5W	SR111-12-xxD-9yy-03-S3	PASS	1	3
12V AR111 Vivid	18.5W	SR111-18-xxD-9yy-03-S3	PASS	1	2
12V AR111 Warm Dim	18.5W	SR111-19-xxDM-9yy/918-01	PASS	1	2

If multiple lamps are installed on one transformer, they need to be connected in parallel. They cannot be installed in series.

Dimmer Compatibility

SORAA Optima 230V to 12V transformer is made to work with trailing edge (reverse phase) phase cut dimmers.

Dimmer compatibility tables with all Soraa 12V lamps are shown from page 3.

For each dimmer, you can see the amount of transformers that were tested per dimmer, and how many lamps per transformer, followed by the results expressed in %.

The % for each transformer/dimmer combination are the % of light output that we were able to dim down to without seeing any problems like flicker/shimmer. Anything 30% or above is considered not compatible and you will see a "NC" in a grey cell.

There might be a minimum wattage load on the dimmer. If this minimum load is not met, there might be compatibility issues.

Maximum number of lamps on a dimmer/transformer

The following need to be considered when determining the amount of lamps on a dimmer/transformer.

1. SORAA tests have been carried out with 1 lamp unless stated otherwise.
2. There is a repetitive, very brief current spike the LED lamp will see twice per cycle. This current spike has to be provided by the transformer and/or dimmer, and will affect the recommended lamp load on each transformer or dimmer.
3. For dimmers rated for LED loads, Soraa recommends following the dimmer manufacturer indications.

Distance between transformer and lamp(s)

12V AC Electronic transformers have a limitation in the length of the wires between transformer and lamp(s). We recommend that the secondary transformer cables are less than 30 cm long

Disclaimer

Compatibility tests are conducted by Soraa only as guidance for the user. All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site.

Results may vary due to variability in component choices and manufacturing processes by the dimmer manufacturers. For more information on the dimmers, please find specs on the manufacturer's website.

**SORAA Optima 230V Electronic 12V transformer with 12V Soraa Vivid MR16 7.5W & 9W lamps - DIMMER
COMPATIBILITY LIST**

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers tested per dimmer	Number of lamps per transformer	Dim (%)	Comments
Aurora		DSP400X	Leading	2	1	NC	
Busch		6523 U-102	Trailing	1, 10	1	8%	
Casambi		CBU-TED	Trailing	1	1	4%	
Clipsal		32ELEDM	Trailing	2	1	7%	
Clipsal		L5504D2U	Adaptive-TE	5, 15	1	7%	
DIGINET		DGLCDM400 (MEDM)	Trailing	2, 15	1	5%	
Elko		315GLE	Trailing	1	1	7%	
ETC	DRd	EELV6	Trailing	6	1	7%	Tested by dimmer manufacturer
Feller		3314.12 FMI.61	Trailing	1, 2, 15	1	10%	
Feller		40200.LED.FMI.61	Trailing	1, 2, 15	1	25%	Limited by dimmer travel
Feller		40300.RC	Trailing	1	1	7%	
Gira		238500 / I01	Adaptive-TE	1, 2, 10	1	11%	Limited by dimmer travel
Govena		PRO-250-LT-LED	Leading	1	1	NC	
Helvar	Digidim	452	Trailing	5, 15	1	5%	
Helvar	Digidim	454	Trailing	5, 15	1	5%	
Honeywell	Inncom	H454.F.CE	Trailing	1, 5, 15	1	12%	
Jung		1224 LED UDE	Trailing	2	1	7%	Limited by dimmer travel
Jung		225 TDE	Trailing	1	1	21%	
LCI		#1770100	Trailing	1, 10	1	NC	
LCI	MTV 400	#1770104	Trailing	1, 10	1	4%	
Legrand		572239	Trailing	1	1	9%	
Lutron	Grafik Eye QS	Grafik Eye QS	Leading	1, 2, 5	1	NC	
Lutron	Grafik Eye QS + Interface	NGRX-ELVI-CE with Grafik Eye QS main unit	Adaptive-TE	Min 1-Max 20	1	9%	Tested by dimmer manufacturer
Lutron	Grafik Integrale	GXI-3104	Trailing	Min 1-Max 12 (per channel). Total per module is 40	1	9%	Tested by dimmer manufacturer
Lutron	Homeworks QS Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D (Gen2) / LQSE-4A-D (Gen2)	Trailing	Min 1-Max 14 (per zone)	1	6%	Tested by dimmer manufacturer
Lutron	Homeworks QS / My Room	LQSE-4A1-D / MQSE-4A1-D / MQSE-3A1 / MQSE-2A1-D	Trailing	Min 1-Max 4	1	9%	Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRK-R25NE-240	Trailing	Min 1-Max 5	1	10%	Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRM-R25NE-240	Trailing	Min 1-Max 5	1	10%	Tested by dimmer manufacturer

**SORAA Optima 230V Electronic 12V transformer with 12V Soraa Vivid MR16 7.5W & 9W lamps - DIMMER
COMPATIBILITY LIST**

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers tested per dimmer	Number of lamps per transformer	Dim (%)	Comments
Lutron	LCP Panel	RPM-4A-230	Adaptive-TE	5	1	6%	
Lutron	RA2 Select	RRK-R25NE-240	Trailing	Min 1-Max 5	1	10%	Tested by dimmer manufacturer
Merten		MEG5136-0000 (SBD315RC)	Trailing	1	1	7%	
MK		K1526	Leading	1	1	NC	
Osram		HTI DALI 315 DIM	Trailing	2	1	12%	Limited by dimmer travel
Philips Dynalite		DGLEDM401	Trailing	1 and 5	1	14%	Limited by dimmer travel
Philips Dynalite		DGTM402	Trailing	5	1	NC	Limited by dimmer travel
Rako		RMT500	Trailing	1	1	4%	
RVE		RV-LED 250	Trailing	5	1	7%	Limited by dimmer travel
Schneider		SBD315RC	Trailing	1	1	7%	
Varilight	V-PRO	JQP401W	Trailing	1, 2, 5	1	8%	(*) Limited by dimmer travel
Vossloh-Schwabe		554591 (5-250W)	Trailing	1 and 2	1	7%	
Vossloh-Schwabe		554592 (5-500W)	Trailing	1	1	7%	
Vossloh-Schwabe		OneDim	Trailing	1 and 2	1	7%	
Yokis		MTV500E / M	Trailing	5	1	9%	(*) Limited by dimmer travel

**SORAA Optima 230V Electronic 12V Soraa MR16 WARM DIM lamps - DIMMER
COMPATIBILITY LIST**

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers tested per dimmer	Number of lamps per transformer	Dim (%)	Comments
Busch		6523 U-102	Trailing	3	1	8%	Limited by dimmer travel
Casambi		CBU-TED	Trailing	3	1	6%	
Feller		3314.12 FMI.61	Trailing	3	1	6%	
Feller		40200.LED.FMI.61	Trailing	3	1	18%	Limited by dimmer travel
Gira		238500 / I01	Adaptive-TE	3	1	12%	Limited by dimmer travel
Helvar	Digidim	452	Trailing	3	1	7%	
Helvar	Digidim	454	Trailing	3	1	8%	
Honeywell	Inncom	H454.F.CE	Trailing	3	1	6%	
LCI		#1770100	Trailing	1, 10	1	NC	
LCI	MTV 400	#1770104	Trailing	1, 3	1	4%	
Lutron	Grafik Eye QS + Interface	NGRX-ELVI-CE with Grafik Eye QS main unit	Adaptive-TE	3	1	8%	
Lutron	Grafik Integrale	GXI-3104	Trailing	1-10 (max per zone)	1	10%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D (Gen2) / LQSE-4A-D (Gen2)	Trailing	1-11 (max per zone)	1	9%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS / My Room	LQSE-4A1-D / MQSE-4A1-D / MQSE-3A1 / MQSE-2A1-D	Trailing	1-3 (max per zone) Total per main unit is 12	1	10%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRK-R25NE-240	Trailing	1-4 (max per zone)	1	9%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRM-R25NE-240	Trailing	1-4 (max per zone)	1	9%	(*) Tested by dimmer manufacturer
Lutron	RA2 Select	RRK-R25NE-240	Trailing	1-4 (max)	1	9%	(*) Tested by dimmer manufacturer
Mode Lighting	Tiger	Trailing edge card	Trailing	3	1	4%	
Philips Dynalite		DGLEDM401	Trailing	3	1	20%	Limited by dimmer travel
Varilight	V-PRO	JQP401W	Trailing	3	1	15%	Limited by dimmer travel
Viribright		80-20EU	Trailing	1	1, 3	9%	
Yokis		MTV500E / M	Trailing	5	1	5%	(*) Limited by dimmer travel

SORAA Optima 230V Electronic 12V transformer with 12V Soraa MR16 Brilliant HL lamps - DIMMER COMPATIBILITY LIST

Dimmer Manuf.	Dimmer family	Dimmer model number	Dimming mode	Number of transformers tested per dimmer	Number of lamps per transformer	Dim (%)	Comments
Busch		6523 U-102	Trailing	3	1	14%	Limited by dimmer travel
Casambi		CBU-TED 150W	Trailing	1-5 (max)	1	0%	(*)
Feller		3314.12 FMI.61	Trailing	3	1	13%	(*)
Feller		40200.LED.FMI.61	Trailing	3	1	8%	
Gira		238500 / I01	Adaptive-TE	3	1	15%	Limited by dimmer travel
Helvar	Digidim	452	Trailing	3	1	7%	(*)
Helvar	Digidim	454	Trailing	3, 5	1	5%	
Honeywell	Inncom	H454.F.CE	Trailing	3	1	26%	(*) Limited by dimmer travel
Jung		1224 LED UDE	Trailing	3, 5	1	6%	Limited by dimmer travel
LCI		#1770100	Trailing	1, 10	1	0%	
Lutron	Grafik Eye QS + Interface	PHPM with Grafik Eye QS main unit	Adaptive-TE	3, 5	1	6%	Limited by dimmer travel
Lutron	Grafik Integrale	GXI-3104	Trailing	1-16 (max per zone)	1	10%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D (Gen2) / LQSE-4A-D (Gen2)	Trailing	1-18 (max per zone)	1	20%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS / My Room	LQSE-4A1-D / MQSE-4A1-D / MQSE-3A1 / MQSE-2A1-D	Trailing	1-5 (max per zone) Total per main unit is 20	1	10%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRK-R25NE-240	Trailing	1-7 (max per zone)	1	10%	(*) Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRM-R25NE-240	Trailing	1-7 (max per zone)	1	10%	(*) Tested by dimmer manufacturer
Lutron	LCP Panel	RPM-4A-230	Adaptive-TE				
Lutron	RA2 Select	RRK-R25NE-240	Trailing	1-7 (max)	1	10%	(*) Tested by dimmer manufacturer
Philips Dynalite		DGLEDM401	Trailing	3, 5	1	13%	Limited by dimmer travel
Tridonic		DALI-PCD 1-300 one4all G2	Trailing	10	1	11%	(*) Limited by dimmer travel
Varilight	V-PRO	JQP401W	Trailing	3, 5	1	8%	Limited by dimmer travel
Yokis		MTV500E / M	Trailing	10	1	9%	(*) Limited by dimmer travel

SORAA Optima 230V Electronic 12V transformer with 12V Soraa Vivid AR111 18.5W lamps - DIMMER COMPATIBILITY LIST

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers tested per dimmer	Number of lamps per transformer	Dim (%)	Comments
Aurora		DSP400X	Leading	2	1	NC	
Clipsal		32ELEDM	Trailing	2	1	9%	Limited by dimmer travel
Clipsal		L5504D2U	Adaptive-TE	5	1	9%	
DIGINET		DGLCDM400 (MEDM)	Trailing	2	1	2%	Limited by dimmer travel
ETC	DRd	EELV6	Trailing	6	1	34%	Tested by dimmer manufacturer
Feller		3314.12 FMI.61	Trailing	2	1	11%	
Feller		40200.LED.FMI.61	Trailing	2	1	24%	Limited by dimmer travel
Gira		238500 / I01	Adaptive-TE	2	1	9%	Limited by dimmer travel
Helvar	Digidim	452	Trailing	5	1	7%	
Helvar	Digidim	454	Trailing	3	1	0%	(*)
Honeywell	Inncom	H454	Trailing	5	1	8%	
Jung		1224 LED UDE	Trailing	2, 3	1	9%	(*) Limited by dimmer travel
LCI	MTV 400	#1770104	Trailing	1, 10	1	1%	Limited by dimmer travel
Lutron	Grafik Eye QS	Grafik Eye QS	Leading			NC	
Lutron	Grafik Eye QS + Interface	NGRX-ELVI-CE with Grafik Eye QS main unit	Adaptive-TE	Min 1-Max 11	1	8%	Tested by dimmer manufacturer
Lutron	Grafik Integrale	GXI-3104	Trailing	Min 1-Max 7 (per channel). Total per module is 40	1	9%	Tested by dimmer manufacturer
Lutron	Homeworks QS Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D (Gen2) / LQSE-4A-D (Gen2)	Trailing	Min 1-Max 7 (per zone)	1	10%	Tested by dimmer manufacturer
Lutron	Homeworks QS / My Room	LQSE-4A1-D / MQSE-4A1-D / MQSE-3A1 / MQSE-2A1-D	Trailing	Min 1-Max 2	1	9%	Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRK-R25NE-240	Trailing	Min 1-Max 3	1	9%	Tested by dimmer manufacturer
Lutron	Homeworks QS	HQRM-R25NE-240	Trailing	Min 1-Max 3	1	9%	Tested by dimmer manufacturer
Lutron	LCP Panel	RPM-4A-230	Adaptive-TE	5	1	9%	
Lutron	RA2 Select	RRK-R25NE-240	Trailing	Min 1-Max 3	1	9%	Tested by dimmer manufacturer

SORAA Optima 230V Electronic 12V transformer with 12V Soraa Vivid AR111 18.5W lamps - DIMMER COMPATIBILITY LIST

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers tested per dimmer	Number of lamps per transformer	Dim (%)	Comments
Mode Lighting	Tiger / Mirage / Evo	Trailing edge card	Trailing	1	1	6%	
Osram		HTI DALI 315 DIM	Trailing	2	1	17%	
Philips Dynalite		DGLEDM401	Trailing	1 and 5	1	16%	Limited by dimmer travel
Philips Dynalite		DGTM402	Trailing	5	1	28%	Limited by dimmer travel
RVE		RV-LED 250	Trailing	5	1	5%	Limited by dimmer travel
Varilight	V-PRO	JQP401W	Trailing	1, 2, 3	1	8%	(*) Limited by dimmer travel
Vossloh-Schwabe		554591 (5-250W)	Trailing	1 and 2	1	10%	
Vossloh-Schwabe		554592 (5-500W)	Trailing	1	1	10%	
Vossloh-Schwabe		OneDim	Trailing	1 and 2	1	10%	
Yokis		MTV500E / M	Trailing	3	1	7%	(*) Limited by dimmer travel

SORAA Optima 230V Electronic 12V transformer with 12V Soraa Vivid AR111 12.5W lamps - DIMMER COMPATIBILITY LIST

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers per dimmer	Number of lamps per transformer	Dim (%)	Comments
Aurora		DSP400X	Leading	2	1	NC	
Clipsal		32ELEDM	Trailing	2	1	12%	Limited by dimmer travel
Clipsal		L5504D2U	Adaptive-TE	5	1	9%	
DIGINET		DGLCDM400 (MEDM)	Trailing	2	1	2%	
ETC	DRd	EELV6	Trailing	6	1	19%	Tested by dimmer manufacturer
Feller		3314.12 FMI.61	Trailing	2	1	14%	
Feller		40200.LED.FMI.61	Trailing	2	1	18%	Limited by dimmer travel
Gira		238500 / I01	Adaptive-TE	2	1	13%	Limited by dimmer travel
Helvar	Digidim	452	Trailing	5	1	7%	
Helvar	Digidim	454	Trailing	5	1	9%	
Honeywell	Inncom	H454	Trailing	5	1	8%	
Jung		1224 LED UDE	Trailing	2	1	12%	Limited by dimmer travel
LCI	MTV 400	#1770104	Trailing	1, 10	1	1%	(*) Limited by dimmer travel
Lutron	Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D	Trailing	5	1	29%	
Lutron	Grafik Eye QS	Grafik Eye QS	Leading	5	1	NC	
Lutron	Grafik Eye QS + Interface	Grafik Eye QS + ELVI interface	Adaptive-TE	5	1	9%	Limited by dimmer travel
Lutron	LCP Panel	RPM-4A-230	Adaptive-TE	5	1	8%	Limited by dimmer travel
Osram		HTI DALI 315 DIM	Trailing	2	1	18%	Limited by dimmer travel
Philips Dynalite		DGLEDM401	Trailing	5	1	19%	Limited by dimmer travel
Philips Dynalite		DGTM402	Trailing	5	1	NC	Limited by dimmer travel
RVE		RV-LED 250	Trailing	5	1	5%	Limited by dimmer travel
Varilight	V-PRO	JQP401W	Trailing	2	1	9%	Limited by dimmer travel
Vossloh-Schwabe		554591 (5-250W)	Trailing	2	1	6%	Limited by dimmer travel
Vossloh-Schwabe		OneDim	Trailing	2	1	3%	Limited by dimmer travel

SORAA Optima 230V Electronic 12V transformer with 12V Soraa Vivid AR111 6W lamps - DIMMER COMPATIBILITY LIST

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers per dimmer	Number of lamps per transformer	Dim (%)	Comments
Aurora		DSP400X	Leading	2	1	NC	
Clipsal		32ELEDM	Trailing	2	1	29%	
Clipsal		L5504D2U	Adaptive-TE	5	1	17%	
DIGINET		DGLCDM400 (MEDM)	Trailing	2	1	16%	
Feller		3314.12 FMI.61	Trailing	2	1	26%	
Feller		40200.LED.FMI.61	Trailing	2	1	NC	Limited by dimmer travel
Gira		238500 / I01	Adaptive-TE	2	1	NC	
Helvar	Digidim	452	Trailing	5	1	8%	
Helvar	Digidim	454	Trailing	5	1	8%	
Honeywell	Inncom	H454	Trailing	5	1	9%	
Jung		1224 LED UDE	Trailing	2	1	NC	
Lutron	Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D	Trailing	5	1	8%	Limited by dimmer travel
Lutron	Grafik Eye QS	Grafik Eye QS	Leading	5	1	NC	
Lutron	Grafik Eye QS + Interface	Grafik Eye QS + ELVI interface	Adaptive-TE	5	1	14%	Limited by dimmer travel
Lutron	LCP Panel	RPM-4A-230	Adaptive-TE	5	1	13%	Limited by dimmer travel
Osram		HTI DALI 315 DIM	Trailing	2	1	23%	Limited by dimmer travel
Philips Dynalite		DGLEDM401	Trailing	5	1	NC	
Philips Dynalite		DGTM402	Trailing	5	1	NC	
RVE		RV-LED 250	Trailing	5	1	NC	
Varilight	V-PRO	JQP401W	Trailing	2	1	13%	
Vossloh-Schwabe		554591 (5-250W)	Trailing	2	1	15%	
Vossloh-Schwabe		OneDim	Trailing	2	1	15%	

SORAA Optima 230V Electronic 12V transformer with 12V Soraa AR111 WARM DIM lamps - DIMMER COMPATIBILITY LIST

Dimmer Manufacturer	Dimmer family	Dimmer model number	Dimming mode	Number of transformers tested per dimmer	Number of lamps per transformer	Dim (%)	Comments
Helvar	Digidim	452	Trailing	3	1	0%	
Helvar	Digidim	454	Trailing	3	1	2%	
Lutron	Grafik Eye QS + Interface	NGRX-ELVI-CE with Grafik Eye QS main unit	Adaptive-TE	3	1	0%	
Lutron	Homeworks QS Energy Savr Node QS (for Quantum and QS systems)	QSNE-4A-D (Gen2) / LQSE-4A-D (Gen2)	Trailing	3	1	NC	
Philips Dynalite		DGLEDM401	Trailing	3	1	10%	
Varilight	V-PRO	JQP401W	Trailing	3	1	10%	
Viribright		80-20EU	Trailing	1	1, 2	3%	
				2	3	4%	
Yokis		MTV500E / M	Trailing	3	1	4%	(*) Limited by dimmer travel

Notes:

- Compatibility tests are conducted by Soraa (unless stated otherwise) under bench conditions as guidance for the user.
- Regards compatibility tests conducted by dimmer manufacturer, please contact Soraa or the manufacturer for more details and/or reports.
- Results at the application site may differ due to variability in usage conditions or in dimmer components/manufacturing.
- If a dimmer is not listed, it does not mean is not compatible, but it has not been tested yet. Please consult with Soraa before making recommendations to the end customer.

--%	Dims to < 20% (of the measured light output)
--%	Dims to 20-30% (of the measured light output)
NC	Not compatible (or dims to >30%)
Blank cell	Not tested