



Electrical compatibility – Warm Dim AR111 12V lamps – Japan

Table of contents

- General compatibility guidelines.....Page 2
- Transformer compatibility.....Page 3
- Dimming compatibility.....Page 4-5

Scope

This document provides the basic guidelines regards electrical compatibility of SORAA 12V AR111 Warm Dim lamps and compatibility tables for transformers and dimmers.

Transformer Compatibility

SORAA 12V AR111 lamps are made to work with 12V AC magnetic (MLV) and electronic (ELV) transformers and 12V DC transformers. Transformer compatibility tables are on this document. If multiple lamps are installed on one transformer, they need to be connected in parallel. They cannot be installed in series.

- 12V AC Magnetic transformers and 12V DC transformers are in general compatible.
- 12V AC Electronic transformers generally have a minimum load, and SORAA recommends using only transformers that have been tested and found compatible. In general we recommend to use transformers with very little or no minimum load (0W). If your transformer is not in the compatibility tables below, it does not mean it is incompatible, but it means that we have not tested it to date, please contact techsupport@soraa.com for guidance.

For transformer-lamp compatibility, Soraa only tests up to 5 transformers per circuit. Consult Soraa, controls provider and transformer manufacturer for latest compatibility when installing 5 or more fixtures per circuit. Lamp performance may vary based on field conditions, including but not limited to THD, shared neutral wires, power-quality. Whenever possible, test lamps in-situ to verify satisfactory performance.

Dimmer Compatibility

SORAA 12V AR111 lamps are made to work with trailing edge (reverse phase) and leading edge (forward phase) phase cut dimmers.

Electronic dimmable transformers need trailing edge dimmers, while Magnetic transformers need leading edge dimmers.

On the dimmer compatibility, the percentages for each transformer/dimmer combination are the percentage of measured light output that we were able to dim down to without seeing any problems like flicker/shimmer. Anything 30% or above is considered not compatible and you will see a "NC" in a grey cell. There might be a minimum wattage load on the transformer/dimmer. If this minimum load is not met, there might be compatibility issues.

Maximum number of lamps on a dimmer/transformer

The following need to be considered when determining the amount of lamps on a dimmer/transformer.

1. SORAA tests have been carried out with 1 lamp unless stated otherwise.
2. There is a repetitive, very brief current spike the LED lamp will see twice per cycle. This current spike has to be provided by the transformer and/or dimmer, and will affect the recommended lamp load on each transformer or dimmer.
3. Ultimately the transformer/dimmer manufacturer is the only one with authority to rate their product, but SORAA can give an Engineering estimate.
4. For transformers, we recommend to use a 1.4 de-rating factor:

For example for a 50W transformer it would mean $50/1.4=35W$ of LED, so an estimated maximum of 1 lamp 18.5W.

5. For dimmers, we recommend to use a 2.0 de-rating factor for leading edge dimmers with magnetic transformers; and a 4.0 de-rating factor for trailing edge dimmers driving Low Voltage lamps on electronic transformers.

For example for a 500W leading edge dimmer it would mean $500/2=250W$ of LED, so an estimated maximum of 13 lamps 18.5W.

For example for a 400W trailing edge dimmer it would mean $400/4=100W$ of LED, so an estimated maximum of 5 lamps 18.5W.

Distance between transformer and lamp(s)

- 12V AC Magnetic transformers and 12V DC transformers do not have a limitation regards the maximum length of the wires between transformer and lamp. Only the voltage drop has to be taken into account (losses because of the inner resistance of the conductors).
- 12V AC Electronic transformers have a limitation in the length of the wires between transformer and lamp(s). This length is usually stated by the transformer manufacturer on its specs or on the transformer itself, and generally it is limited to 2 meters (6 feet).

Disclaimer

Compatibility tests are conducted by Soraa only as guidance for the user. All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site. Results may vary due to variability in component choices and manufacturing processes by the transformer and dimmer manufacturers. For more information on the dimmers/transformers, please find specs on the manufacturer's website.

SORAA WARM DIM AR111 12V - TRANSFORMER COMPATIBILITY LIST - Japan

PASS - The transformer supports one or more lamps up to the maximum wattage;

NC - SORAA does not recommend this transformer for use with its lamps;

2 Lamp Min - The transformer supports two or more lamps up to the maximum lamp wattage limit;

Transformer Brand	Transformer Model	Transformer Wattage	Input Voltage (VAC)	Transformer Type	18.5W
Japan Lighting	JTR-LA1-37-B1	47	100	Electronic DC	PASS
Panasonic	HNK00844 (*)	50	100	Electronic	PASS
Panasonic	HNK00845 (*)	44	100	Electronic	PASS
Tozai Denko	LA1-30-B1	30	100	Electronic	PASS

Transformer compatibility Notes:

- Compatibility tests are conducted by Soraa only as guidance for the user
- All tests are conducted under bench conditions; results may differ from test results depending on conditions at the application site
- Results may vary due to variability in component choices and manufacturing processes by the transformer manufacturer
- For transformer-lamp compatibility, Soraa only tests up to 5 transformers per circuit. Consult Soraa, controls provider and transformer manufacturer for latest compatibility when installing 5 or more fixtures per circuit. Lamp performance may vary based on field conditions, including but not limited to THD, shared neutral wires, power-quality. Whenever possible, test lamps in-situ to verify satisfactory performance.
- If the transformer's minimum wattage is not met, the lamp may only operate under nominal conditions (nominal line voltage and thermal conditions where the lamp is at full power).
- If the fixture/transformer is not listed as tested, please consult with Soraa first before making any recommendations to end customer.
- Above table is for applications where no dimmer is used. If a dimmer is used, the user should consult the Dimmer/Transformer table, or contact Soraa if their desired combination is not listed.
- Transformer maximum load should not be exceeded. Please follow transformer/dimmer manufacturer's guidelines regarding maximum load with LED lamps. To calculate the estimated maximum number of lamps, please download our calculator from the following link:
<https://res.cloudinary.com/soraa/raw/upload/v1452276139/content/max-lamp-load-calculator.xlsx>
 Or following the guidelines stated on page 2 of this document.
- (*) This transformer added to the compatibility list as of this Revision

SORAA WARM DIM AR111 12V - DIMMING COMPATIBILITY LIST - Japan

Transf. manuf. ↓	Transformer model ↓	Transf. type ↓	Number of lamps per transformer ←	Dimmer →	Daiko LZA-90306E	DAIKO LZA-92794	JIMBO NKW-RTE2S0	JIMBO NKW-RLE5S0	Koizumi AE36745E-C	KOIZUMI AE44056E-B	Maxray OP01346-00	Odelic LC 211 (LED)	Panasonic NQ20615	Panasonic WN 575 259	Panasonic WN 575 280K	Panasonic WT 575 72W	Panasonic WTA 575 83W	Panasonic WTC 575 23W	Panasonic WTC 575 28K	Panasonic WTC 575 82W	Panasonic WTC 575 251	Panasonic WTY 521 730W	Panasonic WTY 541 10W	TES LIGHTING TLC-0003
				Dimming Mode →	LE	TE	TE	LE	LE	TE	TE	TE	TE	LE	LE	TE	TE	LE	LE	TE	LE	TE	TE	LE
Japan Lighting	JTR-LA1-37-B1 (*)	ELV-DC	1		7%				4%		7%	5%	5%				0%	7%			4%		4%	8%
MaxRay マックスレイ	OP01010-70 (*)	ELV	1			9%	NC	NC		NC				NC	10%	NC	NC	NC	NC		NC	8%		
Panasonic	HNK00844 (*)	ELV	1			19%	NC	NC		10%				13%	17%	7%	10%	7%	8%	0%		0%	10%	
Panasonic	HNK00845 (*)	ELV	1			NC	NC	NC		NC				NC	NC	9%	7%	NC	NC	7%		NC	NC	
Tozai Denko 東西 電工	LA1-30-B1 (*)	ELV	1		NC	12%	NC	NC	NC	7%	5%	6%	5%	7%	15%	9%	8%	NC	2%	6%	NC	NC	7%	NC

SORAA Warm Dim AR111 12V - DIMMER/TRANSFORMER COMPATIBILITY - Japan

Dimming compatibility Notes:

- Compatibility tests are conducted by Soraa (unless stated otherwise) under bench conditions as guidance for the user; results at the application site may differ due to variability in usage conditions or in dimmer or transformer components/manufacturing.
- Regards compatibility tests conducted by dimmer manufacturer, please contact the manufacturer or Soraa for more details and/or reports.
- If the transformer's minimum wattage is not met, the lamp may only operate under nominal conditions (nominal line voltage and thermal conditions where the lamp is at full power).
- The lamp load (or number of lamps) should meet minimum load requirement of respective dimmer.
- If the dimmer and transformer is not listed, please consult with Soraa before making recommendations to the end customer.
- Transformer/dimmer maximum load should not be exceeded. Please follow transformer/dimmer manufacturer's guidelines regarding maximum load with LED lamps. To calculate the estimated maximum number of lamps, please download our calculator from the following link:
<https://res.cloudinary.com/soraa/raw/upload/v1452276139/content/max-lamp-load-calculator.xlsx>
Or following the guidelines stated on page 2 of this document.
- (*) One or more test results with this transformer added to the compatibility list as of this Revision